

# AE 2990 AFS Handheld Multi Mode Features

## 1. Multi Mode Channel Conversion:

### A. Codes and its Corresponding Mode Channel

<b>Code0:</b>	<b>HAM BANDS 10 + 12 m (AM/FM/SSB 4W)</b>
<b>Code1:</b>	<b>HAM BAND 10 m (AM/FM/SSB 4W)</b>
<b>Code 2:</b>	<b>HAM BAND 12 m (AM/FM/SSB 4W)</b>
<b>Code 3:</b>	<b>450ch. (AM/FM/SSB 4W)</b>
<b>Code 4:</b>	<b>450ch. (AM/FM/SSB 4W “0” Raster 0 Raster)</b>
<b>Code d:</b>	<b>Germany (80 FM4W; 40 AM 1W and SSB 4W).</b>
<b>Code EU:</b>	<b>40AM 1W, 40 FM/SSB 4W</b>
<b>Code E:</b>	<b>40Ch. AM/FM/SSB 4W</b>
<b>Code PL:</b>	<b>40ch. AM/FM/SSB 4W “0” Raster</b>
<b>Code U:</b>	<b>UK; U1 from 1 to 40; U2 from 1 to 40</b> <b>Frequency display is not necessary for UK mode.</b>
<b>Code US:</b>	<b>40ch. AM/SSB 4W (no FM mode allowed in the USA)</b>

### B. Channel Conversion option for CB: Codes: d, EU, E, PL, U and US only

- Turn **Off** the unit (Volume switch off)