

Reggio E. 18 apr 2006

CH POWER modification and 10KHz alan8001 S.doc

RE: ALAN8001 S MODIFICATIONS

RESET +10 KHz

To reset the + 10Khz function, you have to reset the connection of a wire between the + 10 KHz command and the radio.

- Locate the place of the radio where the modification will be done (see picture)
- Locate the yellow wire (in some units, wires can be of different colour) soldered on the back of the + 10Khz command (this wire joins one of the soldering of the + 10Khz command to the main circuit of the radio);
- Locate, in the central part of the yellow wire, the shrink wrap protection isolating the two cut ends of the wire;
- Remove the insulating protection and join the two wires;
- Insulate the connection with the insulating tape.